



GENERAL FEATURES

- 01 Sturdy Movement.
- 02 Accuracy : $\pm 1.5\%$ of F.S.D.
- 03 Linearity : Better than 1% on printed dials.
- 04 Basis sensitivities : $10 \mu\text{A}$ to 5 mA.
- 05 Overload capacity : 10 times F.S.D.
- 06 Size : 65mm round flush
- 07 Pivot : Jewel construction.
- 08 Higher momentary overload can be withstood.
- 09 Phenolic moduled case with glass front to avoid static charge effect
- 10 Knife edge pointer for accurate readings.
- 11 Fitted on bakelite stand with two lock type terminals

STANDARD RANGES

- 01 MILLIAMMETERS : 0-1, 1.5, 3, 5, 6, 10, 15, 20, 25, 30, 40, 50, 60, 100, 150, 200, 250, 300, 500 & 750mA.
- 02 AMMETERS : 0-1, 1.5, 2, 2.5, 3, 5, 6, 10, 15, 20, 25, & 30Amp.
- 03 MILLIVOLTMETERS : 0-100, 150, 200, 250, 300, 500 750mV.
- 04 VOLTMETERS : 0-1, 1.5, 2, 2.5, 3, 5, 6, 10, 15, 20, 25, 30, 40, 50, 60, 75, 100, 125, 150, 200, 250, 300, 500 & 600V (1000 Ohms/Volt)
- 05 GALVANOMETERS : 30-0-30 & 50-0-50 Sensitivity of $20 \mu\text{A}/\text{div}$,
- 06 GALVANOMETERS : 30-0-30 G Push Button Controlled TYPE MO-65PB
- 07 Weight : 0.5 Kg. (Approx)

We are committed to the continuous development of our products, and therefore reserve the right to amend specifications without prior notice.

OMEGA ELECTRONICS

Works:
28E & F, Malviya Industrial Area,
Jaipur-302 017 (INDIA)
Phone: 0141-2751559

E-mail : info@omegaelectronics.net
: omegajipur62@gmail.com

Marketing Division:
B-28, Fateh Singh Scheme, Opp. Rajputana
Palace Sheraton, Jaipur-302006 (INDIA)
Phone : 091-141-2375647, 2379223

www.omegaelectronics.net