



OMEGA TYPE AC DC POWER SUPPLY has been designed specifically for Electrical / Electronics Lab where fixed DC +5Volt At 1Amp, Fixed DC-5V At 1Amp, Variable 0 - 15 V DC at 500mA & 0 to -15V DC At 500mA . AC voltage 0-6-12-18-24 Volt At 300mA or AC Voltage 12V – 6V - 0V-6V-12V at 300mA.

SPECIFICATIONS

- 01 DC Power +5V at 1A ; -5V At 1Amp ,fixed.
- 02 DC 0 to 15V, 500mA variable.
- 03 DC 0 to -15V, 500mA variable.
- 04 AC voltage Fixed: 12V - 6V - 0V - 6V - 12V At 300mA .
or AC voltage 0-6-12-18-24 Volt At 300mA fixed.

FEATURES

- 01 With Built IN Short Proof Regulated Power Supply
- 02 Power On/Off switch with Neon lamp and Fuse
- 03 Just plug in and start to use
- 04 Compact and light-weighted
- 05 For both digital/analog circuits
- 06 Input Voltage 230VAC $\pm 10\%$ At 50Hz
- 07 Size : W 145 x H 140 x D 200 (mm)
- 08 Weight : 4 Kg Approx

LIST OF ACCESSORIES

- 01 DC output wires 1 Meter With 2mm Banana Pin and Small Crocodile Clip Red ----- 4
- 02 DC output wires 1 Meter With 2mm Banana Pin and Small Crocodile Clip Black ----- 1

We are committed to the continuous development of our products, and therefore reserve the right to amend specifications without prior notice.

OMEGA ELECTRONICS