

CURVE TRACER (SEMICONDUCTOR DEVICES) OMEGA TYPE CST-100



OMEGA TYPE CTS-100 CURVE TRACER is a state-of-the-art testing equipment. Dynamic V-I characteristics of a wide range of semiconductor devices - NPN & PNP Transistor, FET, SCR, UJT, Diode, Zener Diode and LED can be displayed on an oscilloscope. The automatic features are the result of sophisticated internal circuitry based on CMOS and linear integrated circuits. The test procedure is fast and simple. Two inputs are provided to enable comparison of two similar devices. Equipment manufacturers can utilize the instrument for comparison/matching devices with standard devices. This low cost equipment is rigid enough to be used as a general purpose test equipment by hobbyists, laboratories & manufacturers.

SPECIFICATIONS

- Semiconductor Device range:
- 01 Bipolar Transistor (NPN & PNP) 02 FET (Junction N & P Type)
- 03 SCR
- 04 UJT (N-Channel)
- 05 ZENÈR DIODE (Upto 50V Vz)
- 06 GERMANIUM & SILICON DIÓDES
- 07 LED
- 01 NUMBER OF CURVES DISPLAYED
- 02 CURRENT STEPS

03 VOLTAGE STEPS

- (a) 4/8 curves switch selectable for Bipolar Transistor and FET. (B) Single line for all other devices.
- Positive or Negative current steps generated internally for Bipolar transistors.
 - Positive or Negative voltage steps of 0.2V, 0.5V, 1V per step selectable by a band switch for FET.
- 04 INTERNAL CLOCK

05 OPERATING VOLTAGE

FEATURES

3-07-202

- 01 Full protection of semi-conductor devices.
- 02 Full protection of internal circuitry.
- 03 Selection of Forward or Reverse characteristics for Zener diodes, diodes & LED by a switch.

230V ± 10% at 50Hz, A.C. Mains

- 04 Ease of operation due to minimum number of panel settings.
- 05 Mains fuse, neon indicator and switch provided.
- 06 For connecting devices two Nos. of 3 lead cables are provided.

400 Hz.

- 07 Weight : 3.600 Kg. (Approx)
- 08 Dimension: W 290 x H 160 x D 230
- 09 Strongly supported by detailed Operating Instructions.

We are committed to the continuous development of our products, and therefore reserve the right to amend specifications without prior notice.

OMEGA ELECTRONICS

Works: 28E & F, Malviya Industrial Area, Jaipur-302 017 (INDIA) Phone: 0141-2751559

E-mail : info@omegaelectronics.net : omegajaipur62@gmail.com

www.omegaelectronics.net

Marketing Division: B-28, Fateh Singh Scheme, Opp. Rajputana Palace Sheraton, Jaipur-302006 (INDIA) Phone : 091-141-2375647, 2379223