

DIGITAL AC VOLT & AMMETER OMEGA TYPE DPM-AC



OMEGA TYPE Digital Panel Meters are compact versatile panel meters (3½ Digit) for digital display of electrical quantities. They are very useful for laboratories, control panel manufacturers, electricity boards, railways, defence establishments etc. They have high accuracy, high resolution, auto polarity on D.C. display, high input impedance, large easily readable LED display of 12.5 mm digit height.

SPECIFICATIONS

01 INPUT CONFIGURATION Bipolar.

02 FULL SCALE RANG E INPUT Specified as against each Type No.

IMPEDANCE ACCURACY

03 TEMPERATURE COEFFICIENT Less than 100 PPM/ °C 04 RESOLUTION 1 in ± 1999 counts 05 SAMPLING RATE (NORMINAL) 3 samples /second

40 dB at 50 Hz 06 N.M.R.R. 07 DISPLAY 31/2 digit 12.5 mm height 7 segment LED type

08 POLARITY INDICATION Automatic.

Available, three least significant digits get blanked in 09 OVER-RANGE CONDITION

over- range condition.

+ 10 °C to + 50 °C. 10 OPERATING TEMPERATURE

230V ± 10% at 50Hz A.C. Mains. 11 POWER REQUIREMENT

12 Weight: 0.6 Kg. (Approx)

13 Strongly supported by detailed Operating Instructions.

OMEGA	FULLSCALE	ACCURACY	INPUT
TYPE NO.	RANGE		IMPEDANCE
AC VOLTMETERS	A SIGN OF QU	JALITY PROD	UCT
DPM-044	199.9 mV	± 0.5% ± 2 digit	10 M ohms
DPM-045	1.999 V	± 0.5% ± 2 digit	10 M ohms
DPM-046	19.99 V	± 0.5% ± 2 digit	10 M ohms
DPM-047	199.9 V	± 0.5% ± 2 digit	10 M ohms
DPM-048	1000 V	± 0.5% ± 2 digit	10 M ohms
ACAMMETERS			
DPM-063	19.99 µA	$\pm 0.5\% \pm 2$ digit	10 K ohms
DPM-064	199.9 µA	$\pm 0.5\% \pm 2 \text{digit}$	1 K ohms
DPM-065	1.999 mA	$\pm 0.5\% \pm 2 \text{digit}$	100 ohms
DPM-066	19.99 mA	$\pm 0.5\% \pm 2 \text{digit}$	10 ohms
DPM-067	199.9 mA	$\pm 0.5\% \pm 2$ digit	1 ohms
DPM-068	1.999 Amp	$\pm 0.5\% \pm 2 \text{digit}$	0.1 ohm
DPM-069	10.00 Amp	$\pm 0.5\% \pm 2 \text{digit}$	0.01ohm

We are committed to the continuous development of our products, and therefore reserve the right to amend specifications without prior notice.

OMEGA ELECTRONICS